

REVISION INFORMATION		
Rev.	Rev. Date	Brief Description



Package Contents



1x 6x8 Multizone Home Audio Controller/Amplifier



1x Expansion Ribbon Cable



1x AC Power Cord



1x Keypad In-Wall Hub Connection Plate




8x Keypad Controllers



1x User Manual



1x Infrared Remote Control



2x AAA Batteries

P/N	44518
Stereo RMS Power (8 Ω)	25 W / stereo per zone
Stereo RMS Power (4 Ω)	50 W / stereo per zone
Bridged (Mono) RMS Power (8 Ω)	100 W per zone
S/N Ratio	> 85 dB A-Weighted
THD	< 0.1%
Frequency Response	20 Hz - 20 kHz
Input Impedance	> 47 kΩ
Input Sensitivity	500 mV for 50 W @ 1 kHz into 4 Ω on one zone 500 mV for 25 W @ 1 kHz into 8 Ω on one zone
Amplifier Protection	Overload, Short Circuit, Thermal
System ON Trigger Voltage	+12 V DC
External Mute Trigger Voltage	+12 V DC
Infrared Frequency	38 kHz
Input Connectors	3.5 mm stereo, RCA, TOSLINK®, RS-232 (DB9)
Output Connectors	Euroblock terminal (up to 14 ga), RCA Pre-out, 3.5 mm mono, RJ45 (keypad hub only)
Power Supply (Switchable)	115 V / 230 V, 50/60 Hz MAX 1250 W
Maximum Power Consumption	1250 W
Maximum Standby Power	22 W
Dimension (W × H × D)	16.9" × 3.5" × 16.4" (430 mm × 89 mm × 416 mm)
Weight	26.5 lbs (12 kg)



DESCRIPTION :
Monoprice™ 8-Zone Home Audio Multizone Controller and Amplifier Kit, NO LOGO

PID # : 44518

DATE :	UNIT : IN/MM	FILE NAME:
--------	--------------	------------

NO.	PART NAME	SPECIFICATION DESCRIPTION	QTY	UNIT